



OVERVIEW

The RCswitch is capable of switching loads or auxiliary items ON/OFF by connecting to your receiver and controlling from any channel on your radio. Making this perfect for switching higher power items on your models such as smoke machines, lights, sound effects, flaps, landing gear, triggering camera shutters etc...

SPECIFICATION

Voltage: 40V
 Current: 15A Continuous
 Current: 50A Peak
 Signal PWM switch on: >1750us
 Signal voltage range: 4.75V to 8.4V
 Weight: 3.2grams
 Dimensions: L25.0 x W12.0 x H3.8 mm

OPERATION

To operate the switch apply a PWM signal over 1750uS the onboard led will light green to indicate the switch is active.

